



Diploma Programme
Programme du diplôme
Programa del Diploma

© International Baccalaureate Organization 2024

All rights reserved. No part of this product may be reproduced in any form or by any electronic or mechanical means, including information storage and retrieval systems, without the prior written permission from the IB. Additionally, the license tied with this product prohibits use of any selected files or extracts from this product. Use by third parties, including but not limited to publishers, private teachers, tutoring or study services, preparatory schools, vendors operating curriculum mapping services or teacher resource digital platforms and app developers, whether fee-covered or not, is prohibited and is a criminal offense.

More information on how to request written permission in the form of a license can be obtained from <https://ibo.org/become-an-ib-school/ib-publishing/licensing/applying-for-a-license/>.

© Organisation du Baccalauréat International 2024

Tous droits réservés. Aucune partie de ce produit ne peut être reproduite sous quelque forme ni par quelque moyen que ce soit, électronique ou mécanique, y compris des systèmes de stockage et de récupération d'informations, sans l'autorisation écrite préalable de l'IB. De plus, la licence associée à ce produit interdit toute utilisation de tout fichier ou extrait sélectionné dans ce produit. L'utilisation par des tiers, y compris, sans toutefois s'y limiter, des éditeurs, des professeurs particuliers, des services de tutorat ou d'aide aux études, des établissements de préparation à l'enseignement supérieur, des fournisseurs de services de planification des programmes d'études, des gestionnaires de plateformes pédagogiques en ligne, et des développeurs d'applications, moyennant paiement ou non, est interdite et constitue une infraction pénale.

Pour plus d'informations sur la procédure à suivre pour obtenir une autorisation écrite sous la forme d'une licence, rendez-vous à l'adresse <https://ibo.org/become-an-ib-school/ib-publishing/licensing/applying-for-a-license/>.

© Organización del Bachillerato Internacional, 2024

Todos los derechos reservados. No se podrá reproducir ninguna parte de este producto de ninguna forma ni por ningún medio electrónico o mecánico, incluidos los sistemas de almacenamiento y recuperación de información, sin la previa autorización por escrito del IB. Además, la licencia vinculada a este producto prohíbe el uso de todo archivo o fragmento seleccionado de este producto. El uso por parte de terceros —lo que incluye, a título enunciativo, editoriales, profesores particulares, servicios de apoyo académico o ayuda para el estudio, colegios preparatorios, desarrolladores de aplicaciones y entidades que presten servicios de planificación curricular u ofrezcan recursos para docentes mediante plataformas digitales—, ya sea incluido en tasas o no, está prohibido y constituye un delito.

En este enlace encontrará más información sobre cómo solicitar una autorización por escrito en forma de licencia: <https://ibo.org/become-an-ib-school/ib-publishing/licensing/applying-for-a-license/>.



International Baccalaureate®
Baccalauréat International
Bachillerato Internacional

Computer science

Standard level

Paper 1

2 May 2024

Zone A afternoon | **Zone B** afternoon | **Zone C** afternoon

1 hour 30 minutes

Instructions to candidates

- Do not open this examination paper until instructed to do so.
- Section A: answer all questions.
- Section B: answer all questions.
- The maximum mark for this examination paper is **[70 marks]**.

6 pages

2224–6912
© International Baccalaureate Organization 2024

Section A

Answer **all** questions.

1. (a) State **one** benefit of using software-as-a-service (SaaS). [1]
(b) State **one** drawback of using software-as-a-service (SaaS). [1]
2. Describe the pilot running method for the implementation of a new system. [2]
3. Describe the purpose of user acceptance testing. [2]
4. Identify **two** methods of providing user documentation. [2]
5. Outline **one** method that can be used to deliver user training. [2]
6. Define the term *peripheral*. [1]
7. State **two** usability issues that could occur when using a cell phone (mobile phone). [2]
8. Identify **two** methods that can be used to improve the accessibility of a computer system for users. [2]
9. (a) Outline the purpose of the memory data register (MDR). [2]
(b) Outline the role of the arithmetic logic unit (ALU). [2]
10. (a) State the binary equivalent of the denary number 37. [1]
(b) State the hexadecimal equivalent of the binary number 10011110. [1]
11. Distinguish between **two** types of primary memory. [2]
12. Identify **two** of the layers of the Open Systems Interconnection (OSI) seven-layer model. [2]

Section B

Answer **all** questions.

13. Different transmission media may be used within a network.

- (a) (i) Identify **two** characteristics of fibre optic cables as a transmission medium. [2]
- (ii) Identify **two** characteristics of wireless transmission. [2]
- (b) Describe how encryption is used to protect data during transmission. [3]
- (c) Explain how data is transmitted using packet switching. [5]
- (d) Explain **one** social implication of changes to working patterns due to the use of a virtual private network (VPN). [3]

14. (a) Define the NOR Boolean operator.

[1]

A car has features that monitor its speed, direction and distance from the car in front. This is shown in **Figure 1**.

Figure 1: Rules to control car motion

Input	Binary representation	Description
A	0	Car is less than 20 metres from the vehicle in front.
	1	Car is 20 metres or more from the vehicle in front.
B	0	Car is travelling in reverse or stationary.
	1	Car is travelling forward.
C	0	Car speed is more than 130 kilometres per hour.
	1	Car speed is 0–130 kilometres per hour.

For example, if the car is travelling forward, input B would have a binary representation of 1.

- (b) Construct a logic diagram with inputs A, B, and C and output Z to represent the following scenario:

Output Z equals 1 when:

- the car is travelling forward AND it is less than 20 metres from the vehicle in front.
OR
- the car speed is more than 130 km per hour.

In all other conditions, output Z equals 0.

[4]

An additional row (input D) is to be added to assist when the car is in reverse or stationary. Input D checks if there are obstructions less than 3 metres from the rear of the car.

- (c) State the rules that need to be added to **Figure 1** to test this condition.

[2]

(This question continues on the following page)

(Question 14 continued)

Information similar to that presented in **Figure 1** could be used to construct decisions and conditions in program design (see **Figure 2**).

Figure 2: Identifiers for car motion rules

Identifier	Description
F	Distance in metres to the vehicle in front
S	Speed of car in kilometres per hour
T	Travelling in a forward direction

- (d) Determine the value of the following expression given that the input values for F, S and T are:

F = 5
S = 30
T = true

$F \geq 25 \text{ AND } S \geq 10 \text{ AND } S \leq 130 \text{ AND } T = \text{true}$

You must show your working.

[2]

- (e) Construct an algorithm in pseudocode that repeats the following steps while the car is moving:
- Input the value for the distance from the vehicle in front.
 - Input the value for the speed of the car.
 - Check the inputs and notify the user if either the distance from the car in front is less than 20 metres or if the speed of the car is more than 130 kilometres per hour.

The algorithm will only terminate when the car stops moving.

[6]

15. (a) Describe **one** standard operation of collections. [2]

The collection RAINBOW holds the names of the main colours of the rainbow along with their order indicator, as follows:

Blue, E, Green, D, Indigo, F, Orange, B, Red, A, Violet, G, Yellow, C

- (b) Construct an algorithm using pseudocode to read the data from RAINBOW and store the names of the colours in a one-dimensional string array, COLOUR, and the order indicators in another one-dimensional string array, ORDER.

The matching colour and order indicator must have the same index in the COLOUR and ORDER arrays. [4]

- (c) Construct an algorithm using pseudocode to sort the contents of the array ORDER into alphabetical order. The indexes for the corresponding data in the two parallel arrays must remain the same after sorting. [5]

- (d) Compare and contrast the bubble sort algorithm and the selection sort algorithm. [4]
-